Prius and Prius plus wiring colours

Prius vehicle *Wiring*

Pink wire of vehicle = Can High

White wire of vehicle = Can Low

OR

Prius/plus vehicle Wiring colours

Pale Blue wire of vehicle = Can High

Green wire of vehicle = Can Low

converter wiring colours



Identify the can bus wires on vehicle they are twisted together
Cut wires on at a time approx 4 cm from plug and taking care not to let the wires short to anything do 1 wire at a time

Loom side

Connect the Yellow wire of converter to the cut CAN HIGH wire Loom side.

Connect the White wire of converter to the cut CAN LOW wire Loom side.

Clock side

Connect the Green wire of converter to the cut CAN HIGH wire Clock side.
Connect the Blue wire of converter to the cut CAN LOW wire Clock side.

Connect Red of converter to 12v and Black of converter to Earth
If you need help advice please call 07951178250